

# AX84 20W PP Poweramp BOM

Revision: 07.08.25

NOTE: Parts for options are not included on this bill of materials.

Item	Quantity	Reference	Value
1	5	C1, C2, C3, C4, C5	47uF/450V
2	1	C6	100uF/100V
3	2	C7, C8	10uF/160V
4	2	C9, C10	0.1uF/400V
5	2	C11, C12	0.1uF/100V
6	1	C13	0.022uF/400V
7	1	R1	Not Used
8	1	R2	3K/5W
9	2	R3, R4	1k5/1W
10	2	R5, R7	180K/1W
11	1	R6	47K/1W
12	1	R8	15K/1W
13	1	R9	68K
14	1	R10	10K
15	1	R11	220R/10W
16	2	R12, R13	5k6
17	2	R14, R15	1K/5W
18	2	R16, R17	1R/1W
19	5	R18, R19, R20, R21, R27	100K
20	2	R22, R24	1M
21	1	R23	470R
22	2	R25, R26	22K
23	1	F1	2A SLO-BLO
24	1	FH1	Fuse Holder
25	1	J1	Power Connector
26	1	J2	Phonejack
27	2	JW1, JW2	Phonejack Isolation Washer
28	1	S1	SW DPDT
29	1	S2	SW SPST
30	5	D1, D2, D3, D4, D5	1N4007
31	1	PL1	Pilot Lamp Assembly And Bulb
32	1	T1	Hammond 270FX
33	1	T2	Hammond 1650F
34	1	L1	Hammond 156L
35	1	SK4	9 Pin Tube Socket
36	2	SK2, SK3	8 Pin Tube Sockets
37	2	V2, V3	6V6
38	1	V4	12AX7
39	1	VR1	50K/2W LIN Mil-spec Locking
40	1	VR2	5K LIN
41	2	TP1, TP2	Red Test Ports
42	1	TP3	Black Test Port
43	1	K1	Knob
44	1	CH1	Chassis

