

AX84 50W PP Poweramp BOM

Revision: 07.08.11

NOTE: Parts for options are not included on this bill of materials.

Item	Quantity	Reference	Value
1	5	C1, C2, C3, C4, C5	47uF/450V
2	1	C6	100uF/100V
3	2	C7, C8	10uF/160V
4	2	C9, C10	0.1uF/400V
5	2	C11, C12	0.1uF/100V
6	1	C13	0.022uF/400V
7	1	R1	Not Used
8	1	R2	3K/5W
9	1	R3	5.6K/1W
10	1	R4	2K/1W
11	2	R5, R7	180K/1W
12	1	R6	47K/1W
13	1	R8	15K/1W
14	1	R9	68K
15	1	R10	39K
16	1	R11	220R/20W
17	2	R12, R13	5.6K
18	2	R14, R15	1K/5W
19	2	R16, R17	1R/1W
20	6	R18, R19, R20, R21, R26, R27	100K
21	2	R22, R24	1.0M
22	1	R23	470R
23	2	R25, R26	22K
24	1	F1	2A SLO-BLO
25	1	FH1	Fuse Holder
26	1	J1	Power Connector
27	1	J2	Phonejack
28	2	JW1, JW2	Phonejack Isolation Washer
29	1	S1	SW DPDT
30	1	S2	SW SPST
31	5	D1, D2, D3, D4, D5	1N4007
32	1	PL1	Pilot Lamp Assembly And Bulb
33	1	T1	Hammond 272JX
34	1	T2	Hammond 1650N
35	1	L1	Hammond 156L
36	1	SK4	9 Pin Tube Socket
37	2	SK2, SK3	8 Pin Tube Sockets
38	2	V2, V3	EL34
39	1	V4	12AX7
40	1	VR1	50K/2W LIN Mil-spec Locking
41	1	VR2	5K LIN
42	2	TP1, TP2	Red Test Ports

43	1	TP3	Black Test Port
44	1	K1	Knob
45	1	CH1	Chassis